



*AIR CORE INDUCTOR

N110 SCHEMATIC

SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

LE111A
 Cone Kit: C8RLE111A
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 6
 Sweep Frequency Hz: 20-1200
 D.C. Resistance Ohms: 5.5 min/6.5 max
 Gap Gauge: .053"
 Notes: Aquaplas On Back Of Cone
 If Not Serviceable, Replace With: LE10H-1
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No. Use as last resort.
 Replace both units in a stereo pair.

Additional Parts Currently Available*:

Dome: 31385
 Mounting Gasket: 21770
 Trim Gasket: 21813

MID RANGE DRIVER:

LE5-10
 Cone Kit: C8RLE510
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 75-3000
 D.C. Resistance Ohms: 4.9 min/6.1 max
 Gap Gauge: .040"
 Notes:
 If Not Serviceable, Replace With: Currently Available or LE5-12

Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes

MID RANGE DRIVER (Cont'd)

Additional Parts Currently Available*:

Dome: 51686
 Mounting Gasket: 21771
 Trim Gasket: 29931

HIGH FREQUENCY DRIVER:

033
 Diaphragm Kit: D8R033
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 5
 Sweep Frequency Hz: 200-1200
 D.C. Resistance Ohms: 3.6 min/4.4 max
 Gap Gauge: .031"
 Notes: Test With Network
 If Not Serviceable, Replace With: No replacement available.
 034 not safe for L110 System.

Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A
 Additional Parts Currently Available*:
 Mounting Gasket: 57754

SYSTEM SPECIFICATIONS:

Nom. Impedance: 8 Ohm
 Power Capacity: 75 Watts Continuous Program
 Crossover Frequencies: 1000 Hz, 4000 Hz
 Sensitivity: 89dB (1 Watt @ 1 Meter)
 Enclosure Dim: 23-1/2" x 14-1/4" x 11-1/4" D
 597mm x 362mm x 286mm
 Shipping Weight: 50 lbs. - 23 kg.
 Additional Parts Currently Available*:
 Binding Posts: Red: 56131
 Black: 56130

*Other parts may also be available. Check with JBL for details.