



## Features

- 8" down-firing cone transducer
- Built-in high-performance 200-watt RMS amplifier
- Wireless 2.4GHz audio signal transmission
- Two automotive-grade finishes available: high-gloss black and high-gloss white

## Specifications

REVEL B8 WIRELESS SUBWOOFER	
Low-frequency Transducer	8" (200mm) down-firing cone
Amplifier Power	200 Watts (continuous), 400 Watts (peak)
Frequency Response	45Hz – 200Hz
Controls	Volume, Phase, Base Boost
Connections	LFE (RCA-type); left and right line-level (RCA-type)
Enclosure Type	Sealed
External Trigger Input Voltage	3-30 Volts, AC or DC
Subwoofer Power Requirement	120V, 60Hz (USA), 220V – 240V, 50/60Hz (EU)
Subwoofer Power Consumption	<0.5W
Subwoofer Dimensions (H x W x D)	13 <sup>29</sup> / <sub>32</sub> " x 10 <sup>1</sup> / <sub>2</sub> " x 10 <sup>1</sup> / <sub>2</sub> " (353mm x 267mm x 267mm)
Subwoofer Weight	19.8 lbs (9kg)
Transmitter Power Requirement	100 – 240V AC, 50/60Hz
Transmitter Power Consumption	<0.5W
Transmitter Unit Dimensions (H x W x D)	1 <sup>3</sup> / <sub>8</sub> " x 5" x 3 <sup>1</sup> / <sub>2</sub> " (35mm x 127mm x 89mm)
Transmitter Unit Weight	0.26 lbs (117g)
Frequency Range	2403 – 2472MHz
Max Transmitting Power	10dBm

