

/ HK 3390

2 x 80W Stereo receiver

Home Solutions



Highlights

- Phono input
- Ultrawide bandwidth
- A/B speaker selection
- Composite video inputs
- Headphone output
- Tape monitor loop
- Two triggered subwoofer outputs
- High-current capability

The HK 3390 was born to make beautiful music, and, like all specialists, it's very good at what it does. It features high-current, ultrawide bandwidth amplification, a signature Harman Kardon® technology that delivers all the subtlety of an original musical performance, whether reproduced from vinyl or your MP3 player of choice. But even specialists enjoy a change of pace from time to time. So the HK 3390 also features four high-quality composite video inputs, and convenient front-panel inputs for video games and portable audio players.

Key Specifications

- Audio Section – Continuous Average Power (FTC), (stereo mode): 80 watts per channel into 8 ohms @ 20Hz – 20kHz, <0.07% THD, both channels driven; High Instantaneous Current capability (HCC): ±42 amps
- Tuner – Usable Sensitivity: IHF 1.3µV/13.5dBf; THD at 1kHz with 100% modulation, (mono): 0.3%; (stereo): 0.4%; FM Adjacent Channel Selectivity: ±400kHz, 70dB; Ultimate (maximum) S/N Ratio (measured at 1mV RF input level), (mono): 70dB; (stereo): 67dB
- Dimensions (H x W x D) and weight: 6-7/16" x 17-3/8" x 15" (163mm x 442mm x 382mm), 20.9 lb (9.5kg)

Depth measurement includes knobs, buttons and terminal connections, unless stated otherwise; height measurement includes feet and chassis, unless stated otherwise.

harman/kardon®
Designed to Entertain.™

/ HK 3390

2 x 80W Stereo receiver

Features

Power

- 80W x 2 into 8 ohms, 20Hz – 20kHz, at <0.07% THD, with all channels driven simultaneously
- High-current (± 42 amps), ultrawide-bandwidth (10Hz – 110kHz) amplifier design

Connectivity

- Dual subwoofer output, with trigger for direct connection to powered subwoofers
- Four A/V inputs with composite video, plus three audio-only inputs
- One composite video monitor output
- Stereo preamp outputs allow the use of an external power amplifier
- Convenient front-panel audio/video input for use with video games or portable players
- One high-quality phono input for connection of record players with an MM cartridge
- Two analog recording outputs (tape and video)
- IR remote extension jacks for system control

Ease of Use

- High-current capability provides the instantaneous current necessary to precisely drive and control nearly any loudspeaker system
- Ultrawide-bandwidth amplifier design for improved transient accuracy and phase linearity
- FM stereo/FM/AM tuner, auto preset, direct-access tuning and 30 presets
- Two-line dot-matrix display for clear visibility
- Dimmer reduces the brightness of the information screen, or switches it off completely
- Tape monitor loop for recording
- Remote A/B speaker switching
- Subwoofer trigger sends switch on/off information to subwoofer
- Two switched AC outlets on the back panel power accessory devices
- Harman Kardon system remote for control of compatible Harman Kardon CD and DVD players

H A Harman International Company

© 2008 Harman International Industries, Incorporated. All rights reserved. Harman Kardon is a trademark of Harman International Industries, Incorporated, registered in the United States and/or other countries. Designed to Entertain is a trademark of Harman International Industries, Incorporated.

All features and specifications are subject to change without notice.

Part No. HK3390USA4/08

Harman Kardon, Inc.
250 Crossways Park Drive, Woodbury, NY 11797
www.harmankardon.com

harman / kardon[®]
Designed to Entertain.™